

Алматы (7273)495-231
 Ангарск (3955)60-70-56
 Архангельск (8182)63-90-72
 Астрахань (8512)99-46-04
 Барнаул (3852)73-04-60
 Белгород (4722)40-23-64
 Благовещенск (4162)22-76-07
 Брянск (4832)59-03-52
 Владивосток (423)249-28-31
 Владикавказ (8672)28-90-48
 Владимир (4922)49-43-18
 Волгоград (844)278-03-48
 Вологда (8172)26-41-59
 Воронеж (473)204-51-73
 Екатеринбург (343)384-55-89

Иваново (4932)77-34-06
 Ижевск (3412)26-03-58
 Иркутск (395)279-98-46
 Казань (843)206-01-48
 Калининград (4012)72-03-81
 Калуга (4842)92-23-67
 Кемерово (3842)65-04-62
 Киров (8332)68-02-04
 Коломна (4966)23-41-49
 Кострома (4942)77-07-48
 Краснодар (861)203-40-90
 Красноярск (391)204-63-61
 Курск (4712)77-13-04
 Курган (3522)50-90-47
 Липецк (4742)52-20-81

Магнитогорск (3519)55-03-13
 Москва (495)268-04-70
 Мурманск (8152)59-64-93
 Набережные Челны (8552)20-53-41
 Нижний Новгород (831)429-08-12
 Новокузнецк (3843)20-46-81
 Ноябрьск (3496)41-32-12
 Новосибирск (383)227-86-73
 Омск (3812)21-46-40
 Орел (4862)44-53-42
 Оренбург (3532)37-68-04
 Пенза (8412)22-31-16
 Петрозаводск (8142)55-98-37
 Псков (8112)59-10-37
 Пермь (342)205-81-47

Ростов-на-Дону (863)308-18-15
 Рязань (4912)46-61-64
 Самара (846)206-03-16
 Санкт-Петербург (812)309-46-40
 Саратов (845)249-38-78
 Севастополь (8692)22-31-93
 Саранск (8342)22-96-24
 Симферополь (3652)67-13-56
 Смоленск (4812)29-41-54
 Сочи (862)225-72-31
 Ставрополь (8652)20-65-13
 Сургут (3462)77-98-35
 Сыктывкар (8212)25-95-17
 Тамбов (4752)50-40-97
 Тверь (4822)63-31-35

Тольятти (8482)63-91-07
 Томск (3822)98-41-53
 Тула (4872)33-79-87
 Тюмень (3452)66-21-18
 Ульяновск (8422)24-23-59
 Улан-Удэ (3012)59-97-51
 Уфа (347)229-48-12
 Хабаровск (4212)92-98-04
 Чебоксары (8352)28-53-07
 Челябинск (351)202-03-61
 Череповец (8202)49-02-64
 Чита (3022)38-34-83
 Якутск (4112)23-90-97
 Ярославль (4852)69-52-93

Россия +7(495)268-04-70

Казахстан +7(7172)727-132

Киргизия +996(312)96-26-47

<https://genpipe.nt-rt.ru/> || gpn@nt-rt.ru

I-95



I-95 UNITS - COMPLETE AND READY TO OPERATE

Item #	Catalog #	Description	Weight
119020	I-95-A	I-95, plus SEVEN 7-1/2 ft. x 5/8" sections (7.5R8), 95-RGH Rear Guide Hose, R-8CS cutter set, PLUS 1-1/2" ClogChopper (R-1-1/2CG).	72 lbs
119030	I-95-C	I-95, plus SIX 15 ft. x 7/8" sections (15R10), 95-RGH Rear Guide Hose, R-10CS cutter set, TB-95 tool box, PLUS 2" ClogChopper (R-2CG-10).	122 lbs
119050	I-95-D	Combines Units A and C.	143 lbs
119070	I-95-E	Same as I-95-D, plus small drum (95-25A) with 25 ft. x 5/16" cable (25HE1-A) installed.	153 lbs

SPECIFICATIONS

Weight:

39 lbs. (18 kg)

Dimensions:

14" deep x 12" wide x 23" high. (35.5 cm x 30.5 cm x 58.4 cm)

Motor:

1/3 hp with forward-off-reverse switch, ten foot power cord, and ground fault circuit interrupter.

Adjustable Chucks:

Has two sets of notches; one for 5/8" cables and one for 7/8" cables.

Switch from one diameter to the other in seconds.

Leather Gloves:

Double palm, for hand protection when guiding cable.

Drum:

(Optional) Holds 25 ft. of 5/16" cable for 1-1/2" to 2" lines, or 35 ft. x 3/8" cable for 2" to 3" lines.

Cables:

"T" slot couplings slide together to lock and uncouple with a pin key.

7.5R8 – 7-1/2 ft. x 5/8" (2.3m x 15.6 mm) for 1-1/4" through 3"

(30 mm – 75 mm) lines up to 125 ft long;

15R10 or 15R10P with Proflex inner core – 15 ft. x 7/8" (4.6 m x 22 mm) for 2" – 4"

(50 mm – 100 mm) lines up to 150 ft. long.

Cutter set for 5/8" cables:

Arrow Head, Boring Gimlet, 1-1/2" U-Cutter and Retrieving Tool.

Cutter set for 7/8" cables:

Spear Head, 2" U-Cutter, 3" U-Cutter, Hook Auger and Retrieving Tool.